



NOTE: Set FUNCTION selector to Supernova Slow or Supernova Stop (usually option 5 or 6).

INSTALLATION NOTES

1. Set door speeds and verify proper door operation prior to final connections of sensors system.
2. Technician MUST WALK TEST to verify function and detection patterns comply with ANSI/BHMA A156.10 requirements.

NOTE:
For Knowing Act applications
all activating devices must connect
to the purple wires of the OC-904.
Dipswitch 3 of the OC-904 must
be in the ON position.

OC-904 Dipswitch Settings Chart		
Dipswitch Settings	OFF	ON
1. Safety Output	N. O.	N. C.
2. Stall Output	N. O.	N. C.
3. Auto/K.A.	Automatic	Knowing Act
4. Future Use		
Fully Automatic		Knowing Act
1. OFF		1. OFF
2. OFF		2. OFF
3. OFF		3. ON
4. OFF		4. OFF

Title: Doromatic Astrowsing Single w/ Elite		Drawing # 01DORASTELI01
Drawing By: JAS	Date: 03-20-08	Sheet: 1 of 1
Optex Technologies Inc. 3882 Del Amo Blvd., Suite 604, Torrance, CA 90503 Office: (800)877-6656, Fax: (310)214-8655		